# Ferrite Mid-Woofer







### **Key features:**

- **GLASS FIBER LOADED PAPER** CONE
- 2 DEMODULATION RINGS, POWERFUL MOTOR STRUC-**TURE**
- HIGH SPL, LOW THD

# Design notes:

The 10FIND is a high efficiency, (97 dB 1watt / 1 meter) 10-inch woofer with linear frequency response characteristics, high power handling capability, while generating ultra low harmonic distortion artifacts. The 10FIND uses a lightweight glass fiber loaded cone assembly along with a high excursion double roll surround. This combination provides a lightweight, yet strong, piston.

Magnetic Circuit REDCATT engineers have developed a ferrite based magnetic circuit, capable of delivering the highest level of performance, providing a consistent, high integrity magnetic flux gap, ultra low distortion characteristic and high efficiency cooling system. The magnetic structure has integrated two aluminum shorting rings. The magnetic circuit design is optimized to generate the minimum amount of flux modulation,

providing exceptional stability.

#### **Specifications:**

General Spees	
Nominal Diameter:	10"
Rated Impedance:	8 ohm
Power handling	
AES Power:	250 watts
Program Power:	500 watts
Peak Power:	1000 watts
Voice Coil	
Diameter:	2.5 in.
Winding wire:	CCAW
Former:	Glass Fiber
Winding height:	13.5 mm

Frequency response & Impedance

T/S Parameters	
Resonant frequency:	66 Hz
Re:	5.5 ohm
Qes:	0.41
Qms:	13.13
Qts:	0.39
Vas:	23.5 liters
Sd:	346 cm2
Sensitivity:	95.81 dB
Mms:	41.3 grams
Bl:	15.5
Le:	0.68 mH

D	1
Design details Surround Material:	Fabric
Cone material:	Paper
Spider:	Nomex
Plate thickness:	8 mm
Peak to peak linear cone displacement	7.7 mm
Overall diameter:	262 mm
Bolt circle diameter:	246 mm
Baffle cutout dia.:	230 mm
Number of mounting holes:	8
Depth (flange to rear):	108.5 mm
Net weight:	4.55kg


10F	FINDX8-033
Recone kits:	
In many cases REDC	•
ohms, 8 ohms and 1	6 ohms versions.

Indicate what impedance do you


need in your request.

Ordering codes:

#### 2D drawing



f)	8-46.5	_	•
		\$246	\$262
	0 0	_,	_,



Frequency response measured on IAC baffle