Neodymium Compression Driver







Key features:

VERY COMPACT DESIGN

 POWERFUL NEODYMIUM MAGNETIC CIRCUIT BEST USE IN HIGH PERFORMING SPEAKER SYSTEMS AND ARRAYS

Design notes:

The 180NCD is a high performance high frequency device ideal for professional loudspeaker systems. In a ultra compact size, the driver,Äôs neodymium based magnetic circuit provides a robust, high force BL field providing precision control of the Polyimide diaphragm assembly. The unit delivers extended frequency response and high power handling through 1.0 inch exit throat. The suspension has

designed and FEM optimized venting features to lover the harmonic distortion. The venting holes also improves the control over the dome movements at low frequencies. REDCATT has developed unique phase plug. Phase plug is FEM optimized to lower the distortion artifacts at mid frequencies.

180NCD ultra compact design ensures the driver can be used in enclosure designs where the space is very limited, such as line array systems. Redcatt has focused on designing an optimized neodymium based magnetic circuit capable of delivering the highest level of performance and value. This effort has resulted in a device that offers uncompromising performance featuring high efficiency, exceptional transient response and controlled distortion characteristics, all that in extremely compact size.

Specifications:


General specs	
Nominal Diamete	r: 2 "
Rated Impedance	: 16 ohm
Power handling	
AES Power:	40 watts
Program Power:	80 watts
Peak Power:	160 watts
Voice Coil	
Diameter:	1.8 in.
Winding wire:	CCAR
Former:	Nomex

T/S Parameters	
Resonant frequency:	1100 Hz
Nominal sensitivity	110 dB
Re:	12.0 ohm
Le:	n/a mH


Design details	
Dome Material:	Polymer
Surround material:	Polymer
Magnet material:	Neodymium
Overall diameter:	75 mm
Bolt circle diameter:	57 mm
Throat diameter:	26mm mm
Number of mounting holes:	4
Depth (front to rear):	46.5 mm
Net weight:	550g

Ordering codes:
180NCDX-086B
Recone kits:
RC180NCDX-086B
In many cases REDCATT
produces 4 ohms, 8 ohms and
16 ohms versions. Indicate
what impedance do you need
in your request.

Frequency response & Impedance



2D drawing



Frequency response measured on IAC baffle