

Key features:

- 4.5 INCH HIGH TEMPERATURE VOICE COIL
- HIGH SOUND PRESSURE LEVEL
- VERY HIGH POWER HAN-DLING

Ordering codes

Recone kits:

Design notes:


Introducing 186FIND, the powerhouse woofer designed for superior audio performance. With a staggering 3,600 watts of peak power and a 4.5" voice coil that can withstand temperatures exceeding 350°C, this woofer is built to impress. Featuring a new paper pulp mixed with glass fibers, high excursion surround, and an extra large spider, it delivers unparalleled longevity and bass. The motor system's high grade ferrite magnet creates a strong symmetrical flux field,

while the extended space below the voice coil allows for maximum excursion. Get ready to be blown away by the 186FIND woofer.

Specifications:

General specs		T/S Parameters	
Nominal Diameter:	18″	Resonant frequency:	33 Hz
Rated Impedance:	8 ohm	Re:	6 ohm
Power handling		Qes:	0.36
AES Power:	1800 watts	Qms:	12.1
Program Power:	3600 watts	Qts:	0.35
Peak Power:	7200 watts	Vas:	174.2 liters
Voice Coil		Sd:	1256 cm2
Diameter:	4.5 in.	Sensitivity:	96 dB
Winding wire:	Copper	Mms:	288 grams
Former:	Glass Fiber	Bl:	30.2
Winding height:	31.8 mm	Le:	1.51 mH

Frequency response & Impedance






info@redcatt.net




2D drawing



In many cases REDCATT produces 4 ohms, 8 ohms and 16 ohms versions. Indicate what impedance do you need in your request.

186FINDX-552A

RC186FINDX-552A



www.redcatt.net